


Name:			
Enrolment No:			
UNIVERSITY OF PETROLEUM AND ENERGY STUDIES End Semester Examination, May 2022			
Course: Antenna & Wave Propagation Program: B.Tech(ECE) Time : 03 hrs.		Semester: VI Course Code: ECEG3041 Max. Marks: 100	
SECTION A (5Qx4M=20Marks)			
S. No.		Marks	CO
Q 1	Design binomial array with 7 elements and find the array factor.	4	CO3
Q2.	Design yagi-uda antenna with 7 elements.	4	CO4
Q3.	Define radio horizon. Calculate the maximum LOS distance and power received between 2 antennas of gains 25 dB each are placed at a height of 16 m and 10 m above the ground if the communication link is to be established when power of 1W is transmitted	4	CO5
Q4.	Design rhombic antenna to produce the maximum beam at 17.5 deg.	4	CO4
Q5.	Find the directivity if $U = U_0 \sin(\pi \sin \theta)$ for $\theta=0$ to $\pi/2$ and $\phi=0$ to 2π .	4	CO1
SECTION B (4Qx10M= 40 Marks)			
Q6	Derive Lorentz gauge condition and explain babinet's and Love's principle.	10	CO1
Q7.	Deduce an expression for f_{muf} for actual and flat earth.	10	CO5
Q8.	Derive the fields radiated by conductor of finite length 'l' carrying the progressive current distribution along the z-axis.	10	CO2
Q9.	Calculate and plot the radiation pattern of linear end fire side array of 12 elements excited uniformly with spacing of $\lambda/4$ between the individual elements. Calculate the directivity.	10	CO3
SECTION-C (2Qx20M=40 Marks)			
Q 10	Derive the fields radiated by Microstrip patch antenna using the cavity model.	20	CO4
Q11a	Design Tchebyshev array with 5 elements to produce -40 dB down the main lobe maxima. Find the array factor and approximate directivity if the spacing between the elements is $3\lambda/8$.	10	CO3
Q11b.	Design a 10-turn helix to operate in the axial mode. For an optimum design, determine the Circumference (in λ_0), pitch angle (in degrees), and separation between turns (in λ_0), Rr, HPBW and Directivity of the helix.	10	CO2